



Application No. 10/623,654
Amendment dated September 18, 2006
Reply to Office Action of April 18, 2006

Docket No.: 0465-1041P

AMENDMENTS TO THE CLAIMS

1-20. (Canceled)

21. (New) A method for controlling a servo operation of an optical recording medium including a non-writable area having a plurality of header fields with at least one header field staggered with respect to another header field, the method comprising:

(a) determining a difference between a first synchronization reference signal included in the one header field and a second synchronization reference signal included in said another header field; and

(b) controlling the servo operation of the optical recording medium based on the determined difference in the step (a).

22. (New) The method of claim 21, wherein the first and second reference signals respectively correspond to read channel 2 signals obtained from the one header field and said another header field, said read channel 2 signals corresponding to a difference between reflected signals obtained by a split photo detector.

23. (New) The method of claim 21, wherein the first and second reference signals comprise VFO (Variable Frequency Oscillator) signals.

24. (New) The method of claim 21, wherein the determined difference between the first and second reference signals represents a radial tilt of the optical recording medium.

25. (New) The method claim 24, wherein the controlling step (b) controls the servo operation of the optical recording medium to compensate the radial tilt based on the determined difference between the first and second reference signals.

26. (New) The method of claim 24, wherein the determining step (a) further includes detecting at least one from an amount and a direction of the radial tilt.

27. (New) The method of claim 26, wherein the controlling step (b) controls the servo operation of the optical recording medium to compensate the radial tilt based on the detected amount and direction of the radial tilt.

28. (New) The method of claim 23, wherein the plurality of header fields include at least first, second, third and fourth header fields, and said one header field corresponds to the first header field and said another header field corresponds to the third header field in which the first header field is staggered with respect to the third header field.

29. (New) The method of claim 28, wherein the determined difference between the first and second reference signals corresponds to a level difference between the VFO signal of the first header field and the VFO signal of the third header field.

30. (New) The method of claim 28, wherein the step (a) determines the difference between the first and second reference signals by comparing a potential difference between a

track center and the VFO signal of the first header field with a potential difference between the track center and the VFO signal of the third header field.

31. (New) The method of claim 28, wherein the step (a) determines the difference between the first and second reference signals by comparing a potential difference between a ground level and the VFO signal of the first header field with a potential difference between the ground level and the VFO signal of the third header field.

32. (New) The method of claim 23, wherein the first and second reference signals are a peak-to-peak value of the corresponding VFO signal.

33. (New) The method of claim 23, wherein the first and second reference signals are at least one from a bottom holding signal and a peak holding signal of the corresponding VFO signal.

33. (New) The method of claim 23, wherein the first and second reference signals are a hold signal of a center of the corresponding VFO signal.

34. (New) The method of claim 24, wherein the step (b) further comprises:

comparing the determined difference of the first and second reference signals with a threshold value.

35. (New) The method of claim 34, further comprising:

(c) controlling the servo operation of the optical recording medium to compensate the radial tilt, if the compared difference is larger than the threshold value.

36. (New) The method of claim 21, wherein the plurality of header fields include at least first, second, third and fourth header fields in which the first and second header fields are staggered with respect to the third and fourth header fields.

37. (New) The method of claim 36, wherein the step (a) determines a difference between a first signal detected from the first and second header fields and a second signal detected from the third and fourth header fields, and the step (b) controls the servo operation of the optical recording medium based on the determined difference between the first and second detected signals.

38. (New) The method of claim 37, wherein the first reference signal corresponds to a signal read from the first header field, the second reference signal corresponds to a signal read from the second header field, a third reference signal corresponds to a signal read from the third header field, and a fourth reference signal corresponds to a signal read from the fourth header field, and

wherein the first signal detected from the first and second header fields is based on the first and second reference signals, and the second signal detected from the third and fourth header fields is based on the third and fourth reference signals.

39. (New) The method of claim 38, wherein the first, second, third and fourth reference signals comprise VFO (Variable Frequency Oscillator) signals.

40. (New) The method of claim 39, wherein the first, second, third and fourth VFO signals correspond to read 2 channels obtained from the first, third, second and fourth header fields, respectively, said read 2 channels corresponding to a difference between reflected signals obtained by a split photo detector.

41. (New) The method of claim 37, wherein the determined difference between the detected first and second signals represents a radial tilt of the optical recording medium.

42. (New) The method claim 41, wherein the controlling step (b) controls the servo operation of the optical recording medium to compensate the radial tilt based on the determined difference between the detected first and second signals.

43. (New) The method of claim 41, wherein the determining step (a) further includes detecting at least one from an amount and a direction of the radial tilt.

44. (New) The method of claim 43, wherein the controlling step (b) controls the servo operation of the optical recording medium to compensate the radial tilt based on the detected amount and direction of the radial tilt.

45. (New) A method for controlling a tilt servo operation of an optical recording medium including a non-writable area having first, second, third and fourth header fields with the first and second header fields being staggered with the third and fourth header fields, the method comprising:

(a) determining at least one from i) a difference value between a signal from first and second reference signals respectively read from the first and second header fields and a signal from third and fourth reference signals respectively read from the third and fourth header fields, and ii) a difference value between the first reference signal and the third reference signal;

(b) detecting at least one from an amount and a direction of a radial tilt of the optical recording medium based on the determining step (a); and

(c) controlling the tilt servo operation to compensate the radial tilt based on the detected amount and/or the detected direction of the radial tilt.

46. (New) The method claim 45, wherein the first, second, third and fourth reference signals comprise VFO (Variable Frequency Oscillator) signal.

47. (New) The method of claim 46, wherein the first, second, third and fourth reference signals respectively correspond to read channel 2 signals obtained from the first, second, third and fourth header fields, respectively, said read 2 channels corresponding to a difference between reflected signals obtained by a split photo detector.

48. (New) A method for controlling a servo operation of an optical recording medium including a non-writable area having first, second, third and fourth header fields in which the

first and second header fields are staggered with the third and fourth header fields, the method comprising:

(a) determining a difference between a VFO (Variable Frequency Oscillator) signal of the first header field and a VFO signal of the third header field; and

(b) controlling the servo operation based on the difference determined in the step (a).

49. (New) An apparatus for controlling a servo operation of an optical recording medium, the optical recording medium including a non-writable area having first, second, third and fourth header fields in which the first and second header fields are staggered with the third and fourth header fields, the apparatus comprising:

a pickup unit to record or read data on/from the optical recording medium;

a signal detector to detect at least one from i) a difference value between a signal from first and second reference signals respectively read from the first and second header fields and a signal from third and fourth reference signals respectively read from the third and fourth header fields, and ii) a difference value between the first reference signal and the third reference signal;

a driving unit to drive the pickup unit; and

a servo controller to control the driving unit based on at least one from the difference values i) and ii) detected by the signal detector.